

AMENDMENTS TO THE CLAIMS

Claim 1 (Withdrawn) A configurable parameter estimator for a pilot channel, the parameter estimator comprising:

an open-loop channel estimator for performing an open-loop phase estimation;

a first filter coupled to the parameter estimator, the first filter for integrating a first signal from the open-loop channel estimator; and

a second filter coupled to the parameter estimator, the second filter for integrating a second signal from the open-loop channel estimator, the first filter and the second filter providing an error-correcting signal.

Claim 2 (Withdrawn) The configurable parameter estimator recited in Claim 1 wherein the open-loop channel estimator further comprises:

a first interface for providing an in-phase portion and a quadrature-phase portion of a first pilot demodulated sequence;

a second interface for providing the in-phase portion and the quadrature-phase portion of a second pilot demodulated sequence;

a first adder coupled to the first interface and the second separator, the first adder for adding the in-phase portion of the first pilot demodulated sequence and the quadrature-phase portion of the second pilot demodulated sequence; and

a second adder coupled to the first interface and the second separator, the second adder for subtracting the quadrature-phase portion of the first pilot demodulated sequence from the in-phase portion of the second pilot demodulated sequence.

Claim 3 (Withdrawn) The configurable parameter estimator recited in claim 1 wherein the first filter and the second filter are a finite impulse response (FIR) that produce an in-phase correction sample and a quadrature-phase correction sample, respectively.

Claim 4 (Withdrawn) The configurable parameter estimator recited in claim 1 wherein the first filter and the second filter have a variable pilot filter length.

Claim 5 (Withdrawn) The configurable parameter estimator recited in Claim 2 further comprising:

a multiplier coupled to the first separator, the multiplier for multiplying a pilot code times the in-phase portion of the code-demodulated sample to create the first pilot demodulated sequence.

Claim 6 (Withdrawn) The configurable parameter estimator recited in Claim 2 further comprising:

a multiplier coupled to the second separator, the multiplier for multiplying a pilot code times a quadrature-phase portion of the code-demodulated sample to create the second pilot demodulated sequence.

Claim 7 (Withdrawn) An electronic device for correcting the phase of a data signal, the electronic device comprising:

a first input for receiving a phase correction signal;

a second input for receiving the data signal; and

a multiplier coupled to the first input and the second input, the multiplier multiplying the phase correction signal with the data signal to produce a phase-corrected data signal.

Claim 8 (Withdrawn) The electronic device recited in Claim 7 further comprising:

an interface coupled to the multiplier, the interface for communicating a real signal corresponding to an m-ary phase.

Claim 9 (Withdrawn) The electronic device recited in Claim 7 further comprising:

a delay device coupled to the first input and the multiplier, the delay device for delaying the data signal.

Claim 10 (Withdrawn) The electronic device recited in Claim 7 further comprising:

a compare circuit coupled to the delay device, a compare circuit for comparing a desired delay with an actual delay, the compare circuit providing a dump enable signal to the delay device.

Claim 11 (Withdrawn) The electronic device recited in Claim 7 wherein the multiplier has complex multiply components for m-ary phase signal components.

Claim 12 (Withdrawn) A configurable demodulator for demodulating a user code from a received signal, the configurable demodulator comprising:

a first multiply-logic device for multiplying a first product code with an encoded data signal to produce a first code demodulated chip sequence, the first product code including at least a user code sequence;

Claim 16 (Withdrawn) The configurable demodulator recited in Claim 12 wherein the first accumulator and the second accumulator each have separate add-logic devices for adding an in-phase portion and a quadrature-phase portion of a signal.

Claim 17 (Withdrawn) A configurable demodulator for demodulating a traffic channel from a received signal, the configurable demodulator comprising:

 a first multiplier for multiplying a traffic code sequence with a first received demodulated sample of the received signal to produce a first demodulated data sequence;

 a first accumulator coupled to a first multiply-logic device, a first accumulator summing the first demodulated data chip sequence to produce a first intermediate demodulated output data sample;

 a second multiplier for multiplying the traffic code sequence with a second intermediate code demodulated sequence to produce a second intermediate code demodulated sample; and

 a second accumulator coupled to the second multiplier-logic device, the second accumulator summing the second intermediate code demodulated sequence to produce the second code-demodulated sample.

Claim 18 (Withdrawn) The configurable demodulator recited in Claim 17 further comprising:

 a first adder coupled to the first accumulator and the second accumulator, the first adder for adding an in-phase component from the first accumulator to a quadrature-phase component from the second accumulator.

Claim 19 (Withdrawn) The configurable demodulator recited in Claim 17 wherein the first multiplier and the second multiplier each include complex multiply components for m-ary phase signal components.

Claim 20 (Withdrawn) The configurable demodulator recited in Claim 17 further comprising:

a compare circuit coupled to the first accumulator and the second accumulator, the compare circuit for comparing an input integration length to a current integration length, the compare circuit providing a dump enable signal to the first accumulator and the second accumulator.

Claim 21 (Withdrawn) A configurable digital coherent demodulator system for demodulating a digital signal, the digital coherent configurable demodulator system comprising:

a configurable traffic channel demodulator for demodulating a baseline channel into a traffic signal; and

a configurable correction device coupled to the configurable traffic channel demodulator, the configurable correction device having a complex multiplier for multiplying the traffic channel with a feed forward phase error correction signal.

Claim 22 (Withdrawn) The configurable digital coherent demodulator system recited in Claim 21 further comprising:

a configurable parameter estimator coupled to the configurable traffic channel demodulator and the configurable correction device, the configurable parameter estimator providing an error estimate of a pilot channel.

Claim 23 (Withdrawn) The configurable digital coherent demodulator system recited in Claim 22 further comprising:

a configurable extended and long code demodulator coupled to the configurable traffic channel demodulator.

Claim 24 (Withdrawn) The configurable digital coherent demodulator system recited in Claim 22 wherein the configurable parameter estimator provides a feed forward correction factor to the correction device.

Claim 25 (Withdrawn) The configurable digital coherent demodulator system recited in Claim 22 wherein the configurable parameter estimator has a configurable comparator circuit for receiving a configurable accumulator length.

Claim 26 (Withdrawn) The configurable digital coherent demodulator system recited in Claim 25 wherein the configurable correction device has an input for receiving a configurable delay value.

Claim 27 (Withdrawn) The configurable digital coherent demodulator system recited in Claim 25 wherein the configurable accumulator length input to the parameter estimator and the configurable delay value input to the correction device are proportional to each other.

Claim 28 (Canceled)

Claim 31 (Currently Amended) ~~The A configurable receiver recited in Claim 28~~ for a CDMA system, the receiver comprising:

an RF/IF stage for receiving an analog signal;

an analog-to-digital (A/D) converter for converting the analog signal to a digital signal;

a chip-matched filter for filtering the digital signal; and

at least one configurable digital coherent demodulator system for feed forward phase correcting the filtered digital signal,

wherein the at least one configurable digital coherent demodulator system comprises a configurable correction device having an input for receiving a configurable delay value which establishes an amount of delay between the configurable correction device receiving a sample of a demodulated signal, which is based on the filtered digital signal, and transmitting the sample.

Claim 32 (Withdrawn) In a configurable parameter estimator, a method for estimating an error in a pilot channel, the method comprising the steps of:

- a) receiving a first code demodulated sample and a second code-demodulated sample, each having an in-phase and a quadrature-phase component;
- b) demodulating the first code demodulated sample and the second code demodulated sample with a pilot code sequence; and
- c) performing an open-loop channel estimate on the first and second code demodulated samples using an open-loop channel estimator.

Claim 33 (Withdrawn) The method recited in Claim 32 further comprising the steps of:

- d) filtering a first signal from the open-loop channel estimator at a first filter; and
 - e) filtering a second signal from the open-loop channel estimator at a second filter,
- wherein the first signal and the second signal represent an error correction signal.

Claim 34 (Withdrawn) The method recited in Claim 32 further comprising the steps of:

- d) receiving a value specifying a variable pilot filter length using the first filter and the second filter.

Claim 35 (Withdrawn) The method recited in Claim 34 further comprising the steps of:

- e) dumping a first sample from the first filter and a second sample from the second filter when the variable pilot filter length has been satisfied.

Claim 36 (Withdrawn) The method recited in Claim 32 wherein demodulating step b) further comprises the steps of:

- b1) multiplying the first code demodulated sample with the pilot code sequence to create a first intermediate sequence; and
- b2) multiplying the second code demodulated sample with the pilot code sequence to create a second intermediate sequence.

Claim 37 (Withdrawn) The method recited in Claim 36 wherein demodulating step b) further comprises- the steps of:

b3) providing an in-phase portion and a quadrature-phase portion of the first intermediate sequence at a first interface;

b4) providing an in-phase portion and a quadrature-phase portion of the second intermediate sequence at a second interface;

b5) adding the in-phase portion of the first intermediate sequence with the quadrature-phase portion of the second intermediate sequence at a first adder; and

b6) subtracting the quadrature-phase portion of the first intermediate sequence from the in-phase portion of the second intermediate sequence at a second adder.

Claim 38 (Withdrawn) A method of correcting the phase of a data signal using a configurable pilot assisted correction device, the method comprising the steps of:

- a) receiving a demodulated output data sample;
- b) receiving a phase correction signal; and
- c) multiplying the demodulated output data sample with the phase correction signal at a multiplier to produce a phase-corrected data signal.

Claim 39 (Withdrawn) The method recited in Claim 38 further comprising the step of:

- d) adding an in-phase portion of the phase-corrected data signal with a quadrature-phase portion of the phase-corrected data signal to produce a real signal.

Claim 40 (Withdrawn) The method recited in Claim 38 further comprising the step of:

Claim 44 (Withdrawn) The method recited in Claim 43 further comprising the steps of:

- f) receiving the first product code of a user code and an in-phase extended code; and
- g) receiving the second product code of the user code and a quadrature-phase extended code.

Claim 45 (Withdrawn) The method recited in Claim 43 further comprising the steps of:

- h) receiving a desired integration length value;
- i) comparing the desired integration length value to a current integration length at a compare circuit; and
- j) providing a dump enable signal to the first accumulator and the second accumulator if the current integration length satisfies the desired integration length.

Claim 46 (Withdrawn) The method recited in Claim 43 wherein multiplying steps b) and d) comprise the steps of:

- multiplying a first m-ary component of a signal at a first complex multiply component; and
- multiplying a second m-ary component of a signal at a second complex multiply device.

Claim 47 (Withdrawn) The method recited in Claim 43 wherein adding steps c) and e) comprise the steps of:

- adding a first m-ary component of a signal at a first adder component;

and adding a second m-ary component of a signal at a second adder component.

Claim 48 (Withdrawn) A method of demodulating a traffic channel from a received signal at a configurable traffic channel demodulator, the method comprising the steps of:

- a) receiving a first code demodulated sample and a second code demodulated sample;
- b) receiving a traffic code sequence;
- c) multiplying the traffic code sequence with the first code demodulated sample at a first multiplier to produce a first demodulated data sequence;
- d) summing the first demodulated data sequence at a first accumulator to produce a first intermediate output data sample;
- e) multiplying the traffic code with the second code demodulated sample at a second multiplier to produce a second code demodulated sequence; and
- f) summing the second code demodulated sequence at a second accumulator to produce a second intermediate output data sample.

Claim 49 (Withdrawn) The method recited in Claim 48 further comprising the steps of:

- g) adding an in-phase component of the first intermediate output data sample to a quadrature-phase component of the second intermediate output data sample at a first adder to obtain the quadrature-phase demodulated output data sample; and
- h) subtracting the in-phase component of the second intermediate output data sample from a quadrature-phase component of the first intermediate output data sample at a second adder to obtain an in-phase demodulated output data sample.

Claim 50 (Withdrawn) The method recited in Claim 48 wherein steps a) and c) further comprise the following steps;

multiplying a first m-ary component of a signal at a first complex multiply component; and

multiplying a second m-ary component of the signal at a second complex multiply device.

Claim 51 (Withdrawn) The method recited in Claim 48 wherein summing steps b) and d) comprise the steps of:

adding a first m-ary component of the signal at a first adder component;

and adding a second m-ary component of the signal at a second adder component.

Claim 52 (Withdrawn) The method recited in Claim 48 further comprising the steps of:

g) receiving a desired integration length value;

h) comparing the desired integration length value to a current integration length at a compare circuit; and

i) providing a dump enable signal to the first accumulator and the second accumulator if the current integration length satisfies the desired integration length.

Claim 53 (Withdrawn) A method of demodulating a digital signal using a configurable digital coherent demodulator system, the method comprising the steps of:

- a) receiving a baseline digital signal at a configurable traffic channel demodulator;
 - b) demodulating the baseline digital signal with a traffic code to obtain a traffic channel;
- and
- c) receiving a feed forward phase error correction signal at a configurable correction device; and
 - d) multiplying the traffic channel by the feed forward phase error correction signal.

Claim 54 (Withdrawn) The method recited in Claim 53 further comprising the step of:

- e) estimating a phase error correction signal of a pilot channel using a configurable parameter estimator.

Claim 55 (Withdrawn) The method recited in Claim 53 further comprising the steps of:

- f) receiving a channel signal at a configurable extended code/long code demodulator;
- and
- g) demodulating an extended code and a long code modulated signal from the complex channel signal using the configurable extended code/long code demodulator.

Claim 56 (Withdrawn) The method recited in Claim 54 further comprising the step of:

- f) feeding forward the phase error correction signal to the configurable correction device.

